


MINI DIP39, 31.0x54.5 **CASE MODGC** ISSUE A

12.20 12.7


DATE 19 MAR 2019


NOTES


- DIMENSIONING AND TOLERANCING PER. ASME Y14.5M, 2009.
- ASPIE 144.5M, 2009.
 CONTROLLING DIMENSION: MILLIMETERS
 DIMENSION b and c APPLY TO THE PLATED LEADS
 AND ARE MEASURED BETWEEN 1.00 AND 2.00
 FROM THE LEAD TIP.




	MILLIMETERS			
DIM	MIN.	NDM.	MAX.	
Ε	30.90	31.00	31.10	
E1	33.50 REF			
E2	26.14 REF			
E3	12.35 REF			
E4	8.00 REF			
E5	35.40	35.90	36.40	
u	2.81 REF			
e1	7.62 BSC			
e2	6.60 BSC			
e 3	3.30 BSC			
e4	5.35 REF			
e5	6.10 BSC			
e6	8.02 REF			
e7	1.78 BSC			
e8	10.35 REF			
e9	10.25 REF			
e10	3.60 REF			
e11	1.00 REF			
e12	0.89 BSC			
F	3.20	3.30	3.40	
F1	1.40	1.50	1.60	
L	5.60 REF			









GENERIC MARKING DIAGRAM*

XXXXXXXXXXXXXXXXX **ZZZATYWW**

XXXXX = Specific Device Code

= Assembly Lot Code ΑT = Assembly & Test Location

= Year = Work Week \/\/\/

*This information is generic. Please refer to device data sheet for actual part marking. Pb-Free indicator, "G" or microdot " • ", may or may not be present. Some products may not follow the Generic Marking.

DOCUMENT NUMBER:	98AON91300G	Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red.	
DESCRIPTION:	MINI DIP39, 31.0x54.5		PAGE 1 OF 1

ON Semiconductor and unare trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. ON Semiconductor does not convey any license under its patent rights nor the rights of others.